

FRONIUS PRIMO

/ Optimised energy management.



/ SnapINverter Technology



/ Integrated data communication



/ SuperFlex Design



/ Dynamic Peak Manager



/ Smart Grid Ready



/ The Fronius Primo in power categories from 3.0 to 8.2 kW perfectly completes the new SnapINverter generation. This single-phase device is the ideal inverter for residential systems. Its innovative SuperFlex Design provides maximum flexibility in system design, while the SnapINverter mounting system makes installation and maintenance easier than ever before. The included communication package, with WLAN, energy management, several interfaces and much more, allows the Fronius Primo to communicate with the user, the PV system and the grid.

TECHNICAL DATA FRONIUS PRIMO (3.0-1, 3.5-1, 3.6-1¹⁾, 4.0-1, 4.6-1¹⁾)

INPUT DATA	PRIMO 3.0-1	PRIMO 3.5-1	PRIMO 3.6-1 ¹⁾	PRIMO 4.0-1	PRIMO 4.6-1 ¹⁾
Max. input current ($I_{dc \max 1} / I_{dc \max 2}$)			12.0 A / 12.0 A		
Max. array short circuit current (MPP_1/MPP_2)			18.0 A / 18.0 A		
Min. input voltage ($U_{dc \min}$)			80 V		
Feed-in start voltage ($U_{dc \text{ start}}$)			80 V		
Nominal input voltage ($U_{dc,r}$)			700 V		
Max. input voltage ($U_{dc \max}$)			1,000 V		
Usable MPP voltage range ($U_{mpp \min} - U_{mpp \max}$)			80 V - 800 V		
MPP voltage range at nominal power ($U_{mpp \min} - U_{mpp \max}$)		200 - 800 V		210 - 800 V	240 - 800 V
Number of MPP trackers			2		
Number of DC connections			2 + 2		

OUTPUT DATA	PRIMO 3.0-1	PRIMO 3.5-1	PRIMO 3.6-1 ¹⁾	PRIMO 4.0-1	PRIMO 4.6-1 ¹⁾
AC nominal output ($P_{ac,r}$)	3,000 W	3,500 W	3,680 W	4,000 W	4,600 W
Max. output power	3,000 VA	3,500 VA	3,680 VA	4,000 VA	4,600 VA
AC output current ($I_{ac \text{ nom}}$)	13.0 A	15.2 A	16.0 A	17.4 A	20.0 A
Grid connection (voltage range)	1 - NPE 220 V / 230 V (180 V - 270 V)				
Frequency (frequency range)	50 Hz / 60 Hz (45 - 65 Hz)				
Total harmonic distortion	< 5 %				
Power factor ($\cos \phi_{ac,r}$)	0.85 - 1 ind. / cap.				

¹⁾ Available upon request, conditions apply.

TECHNICAL DATA FRONIUS PRIMO (3.0-1, 3.5-1, 3.6-1, 4.0-1, 4.6-1)

GENERAL DATA	PRIMO 3.0-1	PRIMO 3.5-1	PRIMO 3.6-1 ¹⁾	PRIMO 4.0-1	PRIMO 4.6-1 ¹⁾
Dimensions (height x width x depth)	645 x 431 x 204 mm				
Weight	21.5 kg				
Degree of protection	IP 65				
Protection class	1				
Overvoltage category (DC / AC) ²⁾	2 / 3				
Night time consumption	< 1 W				
Inverter design	Transformerless				
Cooling	Regulated air cooling				
Installation	Indoor and outdoor installation				
Ambient temperature range	-40 - +55 °C				
Permitted humidity	0 - 100 %				
Max. altitude	4,000 m				
DC connection technology	2x DC+1, 2x DC+2 and 4x DC- screw terminals 2.5 - 16 mm ²				
Mains connection technology	3-pole AC screw terminals 2.5 - 16 mm ²				
Certificates and compliance with standards	DIN V VDE 0126-1-1/A1, IEC 62109-1/-2, IEC 62116, IEC 61727, AS 3100, AS 4777-2, AS 4777-3, G83/2, G59/3, CEI 0-21				

EFFICIENCY	PRIMO 3.0-1	PRIMO 3.5-1	PRIMO 3.6-1 ¹⁾	PRIMO 4.0-1	PRIMO 4.6-1 ¹⁾
Max. efficiency	97.6 %	97.7 %	97.7 %	97.7 %	97.8 %
European efficiency (η_{EU})	95.2 %	95.6 %	95.7 %	96.0 %	96.3 %
MPP adaptation efficiency	> 99.9 %				


PROTECTIVE DEVICES	PRIMO 3.0-1	PRIMO 3.5-1	PRIMO 3.6-1 ¹⁾	PRIMO 4.0-1	PRIMO 4.6-1 ¹⁾
DC insulation measurement	Yes				
Overload behaviour	Operating point shift. Power limitation				
DC disconnecter	Yes				

INTERFACES	PRIMO 3.0-1	PRIMO 3.5-1	PRIMO 3.6-1 ¹⁾	PRIMO 4.0-1	PRIMO 4.6-1 ¹⁾
WLAN / Ethernet LAN	Fronius Solar.web, Modbus TCP SunSpec, Fronius Solar API (JSON)				
6 inputs and 4 digital in/out	Interface to ripple control receiver				
USB (A socket) ³⁾	Datalogging, inverter update via USB flash drive				
2x RS422 (RJ45 socket) ³⁾	Fronius Solar Net				
Signalling output ³⁾	Energy management (potential-free relay output)				
Datalogger and Webserver	Included				
External input ³⁾	S0-Meter Interface / Input for overvoltage protection				
RS485	Modbus RTU SunSpec or meter connection				


¹⁾ Available upon request, conditions apply. ²⁾ According to IEC 62109-1. ³⁾ Also available in the light version.

Further information regarding the availability of the inverters in your country can be found at www.fronius.com.

FRONIUS PRIMO 8.2-1 EFFICIENCY CURVE



FRONIUS PRIMO 8.2-1 TEMPERATURE DERATING



TECHNICAL DATA FRONIUS PRIMO (5.0-1, 5.0-1 AUS, 6.0-1, 8.2-1)

INPUT DATA	PRIMO 5.0-1 ¹⁾	PRIMO 5.0-1 AUS	PRIMO 6.0-1	PRIMO 8.2-1
Max. input current (I _{dc max 1} / I _{dc max 2})	12.0 A / 12.0 A	18.0 A / 18.0 A		
Max. array short circuit current (MPP ₁ /MPP ₂)	18.0 A / 18.0 A	27.0 A / 27.0 A		
Min. input voltage (U _{dc min})	80 V			
Feed-in start voltage (U _{dc start})	80 V			
Nominal input voltage (U _{dc,r})	700 V			
Max. input voltage (U _{dc max})	1,000 V			
Usable MPP voltage range (U _{mpp min} – U _{mpp max})	80 V - 800 V			
MPP voltage range at nominal power (U _{mpp min} – U _{mpp max})	240 - 800 V			270 - 800 V
Number of MPP trackers	2			
Number of DC connections	2 + 2			

OUTPUT DATA	PRIMO 5.0-1 ¹⁾	PRIMO 5.0-1 AUS	PRIMO 6.0-1	PRIMO 8.2-1
AC nominal output ($P_{ac,r}$)	5,000 W	4,600 W	6,000 W	8,200 W
Max. output power	5,000 VA	5,000 VA	6,000 VA	8,200 VA
AC output current ($I_{ac\ nom}$)	21.7 A	21.7 A	26.1 A	35.7 A
Grid connection (voltage range)	1 - NPE 220 V / 230 V (180 V - 270 V)			
Frequency (frequency range)	50 Hz / 60 Hz (45 - 65 Hz)			
Total harmonic distortion	< 5 %			
Power factor ($\cos\ \varphi_{ac,r}$)	0.85 - 1 ind. / cap.			

GENERAL DATA	PRIMO 5.0-1 ¹⁾	PRIMO 5.0-1 AUS	PRIMO 6.0-1	PRIMO 8.2-1
Dimensions (height x width x depth)	645 x 431 x 204 mm			
Weight	21.5 kg			
Degree of protection	IP 65			
Protection class	1			
Overvoltage category (DC / AC) ²⁾	2 / 3			
Night time consumption	< 1 W			
Inverter design	Transformerless			
Cooling	Regulated air cooling			
Installation	Indoor and outdoor installation			
Ambient temperature range	-40 - +55 °C			
Permitted humidity	0 - 100 %			
Max. altitude	4,000 m			
DC connection technology	2x DC+1, 2x DC+2 and 4x DC- screw terminals 2.5 - 16 mm ²			
Mains connection technology	3-pole AC screw terminals 2.5 - 16 mm ²			
Certificates and compliance with standards	DIN V VDE 0126-1-1/A1, IEC 62109-1/-2, IEC 62116, IEC 61727, AS 3100, AS 4777-2, AS 4777-3, G83/2, G59/3, CEI 0-21			

¹⁾ Available upon request, conditions apply. ²⁾ According to IEC 62109-1. Further information regarding the availability of the inverters in your country can be found at www.fronius.com.

EFFICIENCY	PRIMO 5.0-1	PRIMO 5.0-1 AUS	PRIMO 6.0-1	PRIMO 8.2-1
Max. efficiency	97.8 %	97.8 %	97.8 %	97.8 %
European efficiency (η_{EU})	96.4 %	96.4 %	96.7 %	97.2 %
MPP adaptation efficiency	> 99.9 %			

PROTECTIVE DEVICES	PRIMO 5.0-1	PRIMO 5.0-1 AUS	PRIMO 6.0-1	PRIMO 8.2-1
DC insulation measurement	Yes			
Overload behaviour	Operating point shift, power limitation			
DC disconnecter	Yes			

INTERFACES	PRIMO 5.0-1	PRIMO 5.0-1 AUS	PRIMO 6.0-1	PRIMO 8.2-1
WLAN / Ethernet LAN	Fronius Solar.web, Modbus TCP SunSpec, Fronius Solar API (JSON)			
6 inputs and 4 digital in/out	Interface to ripple control receiver			
USB (A socket) ¹⁾	Datalogging, inverter update via USB flash drive			
2x RS422 (RJ45 socket) ¹⁾	Fronius Solar Net			
Signalling output ¹⁾	Energy management (potential-free relay output)			
Datalogger and Webserver	Included			
External input ¹⁾	S0-Meter Interface / Input for overvoltage protection			
RS485	Modbus RTU SunSpec or meter connection			

¹⁾ Also available in the light version.

PERTH SOLAR WAREHOUSE

/ Perfect Welding / Solar Energy / Perfect Charging

WE HAVE THREE DIVISIONS AND ONE PASSION: SHIFTING THE LIMITS OF POSSIBILITY.

/ Whether welding technology, photovoltaics or battery charging technology – our goal is clearly defined: to be the innovation leader. With around 3,000 employees worldwide, we shift the limits of what's possible - our record of over 1,000 granted patents is testimony to this. While others progress step by step, we innovate in leaps and bounds. Just as we've always done. The responsible use of our resources forms the basis of our corporate policy.

Further information about all Fronius products and our global sales partners and representatives can be found at www.fronius.com

v04 Nov 2014 EN

Fronius Australia Pty Ltd.
90-92 Lambeck Drive
Tullamarine VIC 3043
Australia
pv-sales-australia@fronius.com
www.fronius.com.au

/ Perfect Welding / Solar Energy / Perfect Charging



SHIFTING THE LIMITS



FRONIUS SNAPINVERTERS SMARTER, LIGHTER, MORE FLEXIBLE

FRONIUS GALVO, PRIMO, SYMO, SYMO HYBRID & ECO

A range for all applications. A range for all systems. A range for easy installation.

The Fronius SnapInverter range represents the latest stage in the evolution of inverter technology:

/ Smarter: Inbuilt WLAN monitoring, easy commissioning, energy management function

/ Lighter: Light weight, easy snap-in installation, less installation time and cost, inbuilt DC isolator

/ More flexible: Generous MPPT voltage range, SuperFlex design, Smart Grid ready, future-proof upgradeability

Be impressed: visit www.fronius.com.au

FRONIUS SNAPINVERTERS

Smarter, Lighter, More Flexible

/ With the SnapINverter product range, Fronius covers the entire spectrum of market requirements, from 1.5 to 27 kW. Whether for a single-family home or a large photovoltaic (PV) system, the comprehensive SnapINverter portfolio contains the perfect device. Customers opting for a Fronius SnapINverter are not only rewarded with a smart inverter that maximises yield, but also with the quality assurance of a company that has been leading the way since 1945. With the Fronius “Smarter, Lighter, More Flexible” SnapINverter range, future-proof comes as standard, and that’s just the beginning.




SMARTER




WI-FI SYSTEM MONITORING

/ The Fronius SnapINverter range efficiently meets data communication and system monitoring needs. An integrated Datamanager ensures easy connection to the internet via Wi-Fi or Ethernet. Keep an eye on your yield using your PC, smart phone or tablet, without any extra cost.



SMART GRID READY

/ As the number of decentralised energy generators rises, so too does the need for an intelligent power grid. In the near future, grid operators will impose new requirements on local generators including photovoltaic systems - requirements the Fronius SnapINverter range already meets today.




- / Future-proof
- / Meets present & future grid connection requirements
- / Helps to support and improve grid stability



ENERGY MANAGEMENT FUNCTION

/ With an integrated energy management function, the Fronius SnapINverter range provides a solution for optimising the self-consumption of generated solar power. The energy management function allows power to be directed to a specific electrical appliance, fast-tracking your payback.




OPEN DATA COMMUNICATION

/ It is easy to connect Fronius SnapINverters to components from third party suppliers. The open SunSpec Modbus TCP, RTU (RS485) and JSON protocols provide a simple way of establishing a data connection to other systems such as BMS, SCADA and home automation.



PROACTIVE SERVICE

/ Trained by Fronius, Fronius Service Partners (FSPs) can remotely monitor a PV system using Fronius Solar.web. In the event of a fault, FSPs receive instant notification so they can react immediately to ensure maximum up-time. FSPs have a reserve of spare parts ready to get a PV system back up and running with one trip to site, and thanks to Fronius monitoring capabilities FSPs can also assist with upgrading to a customised battery solution.



- / Fastest service available
- / Protect your investment
- / Nationwide Fronius Service Partners
- / Remote system diagnosis
- / One-trip-to-site service
- / Future-proof system integration



DC ISOLATOR

/ The integrated DC isolator is compliant with installation standard AS/NZS 5033*. No additional DC isolator adjacent to the inverter is required, which saves time and cost.

*Check the Fronius Australia website for technical datasheets outlining installation suitability.

LIGHTER



LIGHT WEIGHT

/ The Fronius SnapINverter range is up to 50% lighter than comparable inverters*. This, in combination with the snap-in design, allows for quick & easy installation.

*Findings from an internal study carried out June 2015.




- / Snap-in design is quick and easy to install
 - / Installation can be performed by one person*
 - / Lower installation costs
 - / Convenient, low-cost maintenance
- *Please check work safety regulations.*

MORE FLEXIBLE



SUPERFLEX TECHNOLOGY

/ Fronius Superflex technology makes designing a PV system easier than ever. The low starting and very broad voltage range of the two MPPTs allows connection of highly asymmetric configurations. This enables the designer to solve most shading issues, including multiple orientated or partly shaded roofs. In some cases even a 1:9 ratio between MPPT1 and MPPT2 is possible.



- / High system design flexibility
- / Most module configurations can be used
- / Optimised performance for shading



SOLAR BATTERY OPTIONS

/ Batteries can easily be added to any PV system that uses a Fronius SnapINverter, either in AC coupled or DC coupled system architecture*. With this future-proof concept, Fronius ensures that every system is primed to integrate storage. Fronius or Tesla batteries can be added at any time, and to help decide which battery size to choose, Fronius Solar.web tracks energy usage** and production.

*Depending on which SnapINverter is chosen. **Consumption monitoring with installation of additional Fronius Smart Meter.



DYNAMIC PEAK MANAGER

/ Even in partially shaded conditions the Fronius Dynamic Peak Manager always finds the maximum output power, ensuring that the inverter is always operating at the point of maximum output. Get up to 4 per cent more yield from a system that has to contend from time to time with shade.

THE FRONIUS SNAPINVERTER RANGE

/ Smarter, Lighter, More Flexible

SYMO HYBRID

/ The personal storage solution

/ The flexible, future-proof platform perfect for battery storage integration. Three phase.

/ 3.0 to 5.0 kW



SYMO

/ Unrivaled 3-phase technology

/ The super flexible, three phase inverter for commercial applications

/ 3.0 to 20.0 kW



PRIMO

/ Optimised energy management

/ The optimal single phase inverter for self-consumption management

/ 3.0 to 8.2 kW



GALVO

/ Repowering

/ The perfect single phase replacement inverter with high frequency transformer topology

/ 1.5 to 3.0 kW



FRONIUS SNAPINVERTER GENERATION

ECO

/ Project optimisation

/ The high power density, three phase inverter for large scale commercial installations

/ 25.0 to 27.0 kW



FRONIUS SNAPINVERTERS INTEGRATED FEATURES

/ Inbuilt features at a glance

	GALVO	PRIMO	SYMO	SYMO HYBRID	ECO
Energy management function inbuilt	✓	✓	✓	✓	✓
Multi MPPTs	-	✓	✓	-	-
Extra broad MPPT voltage window	✓	✓	✓	✓	-
Dynamic Peak Manager: Shading resistant MPPT	-	✓	✓	✓	✓
Suitable for installations under 600V DC	✓	✓	✓	✓	-
Easy installation	✓	✓	✓	✓	✓
DC isolator inbuilt	✓	✓	✓	✓	✓
WLAN monitoring inbuilt	✓	✓	✓	✓	✓
Remote monitoring	✓	✓	✓	✓	✓
Quick commissioning	✓	✓	✓	✓	✓
Smart Grid Ready	✓	✓	✓	✓	✓
Proactive Service Ready	✓	✓	✓	✓	✓
Galvanic Isolation	✓	-	-	-	-

FRONIUS SNAPINVERTER PERFORMANCE DATA

/ One generation for any application

	GALVO	PRIMO	SYMO	SYMO HYBRID	ECO
AC Output power	1.5 – 3.0kVA	3.0 – 8.2kVA	3.0 – 8.2kVA, 10.0 – 20.0kVA	3.0, 4.0, 5.0kVA	25.0, 27.0kVA
Technology	HF Transformer	Transformerless	Transformerless	Transformerless	Transformerless
Number of phases	1	1	3	3	3
Max input voltage	420V*, 550V*	1000V	1000V	1000V	1000V
DC start up voltage	120V*, 165V*	80V	150V*, 200V*	150V	580V
Number of MPP trackers usable	1	2	1*, 2	1	1
MPP voltage range	120 – 335V*, 165 – 440V*	80 – 800V	150 – 800V*, 200V – 800V*	150 – 800V	580 – 850V
Optimised tracking algorithm	No	Yes	Yes	Yes	No
Max efficiency	96.1%	97.8%	98.1%	97.6%	98.7%
Degree of protection	IP 65	IP 65	IP 65*, IP 66*	IP 65	IP 66
Weight	16.8kg	21.5kg	16.0kg*, 19.9kg*, 21.9kg*, 34.8kg*, 43.4kg*	22.0kg	35.7kg
Power factor	0.85 - 1 ind./cap.	0.85 - 1 ind./cap.	0.70 - 1 ind./cap.* 0.85 - 1 ind./cap.*	0.85 - 1 ind./cap.	0.0 - 1 ind./cap.
Dimensions (h x w x d mm)	645 x 431 x 204	645 x 431 x 204	645 x 431 x 204* 725 x 510 x 225*	645 x 431 x 204	725 x 510 x 225

* Depends on specific inverter model. Please refer to specific datasheet for more information.

ACCESSORIES AND SOLUTIONS


FRONIUS SMART METER

/ Thanks to its monitoring capabilities, the Fronius Smart Meter plays a key role in making a PV system storage ready. Combined with Fronius Solar.web, the Fronius Smart Meter presents a clear overview of power consumption, feed-in and surplus energy, enabling improved energy management and giving accurate information on future battery requirements.

SOLAR.WEB

/ PV systems can be monitored, analysed and compared quickly and easily using the Fronius Solar.web online portal. Up-to-date system data can be accessed at any time and is clearly presented via a user-friendly range of analysis functions. Solar.web is also a convenient platform for adjusting system configurations.

Self-sufficiency
100%



/ Battery Charging Systems / Welding Technology / Solar Electronics

WE HAVE THREE DIVISIONS AND ONE PASSION: SHIFTING THE LIMITS.

/ Whether Battery Charging Systems, Welding Technology or Solar Electronics - our goal is clearly defined: to be the technology and quality leader. With around 3,000 employees worldwide, we shift the limits of what's possible - our more than 850 active patents are testimony to this. While others progress step by step, we innovate in leaps and bounds. Further information about all Fronius products and our global sales partners and representatives can be found at www.fronius.com

**PERTH SOLAR
WAREHOUSE**

Fronius Australia Pty Ltd.
90-92 Lambeck Drive
Tullamarine VIC 3043
Australia
pv-sales-australia@fronius.com
www.fronius.com.au

Fronius International GmbH
Froniusplatz 1
4600 Wels
Austria
pv@fronius.com
www.fronius.com

v02 2012 EN

Text and images correspond to the current state of technology at the time of printing. Subject to modifications. All information is without guarantee in spite of careful editing. Liability excluded. Copyright © 2011 Fronius. All rights reserved.